

UT120 SERIES

Pocket Size Digital Multimeters

UT120 series multimeters are designed for DIYers and electronics engineers to troubleshoot electronics systems development and electronics circuits. It is a simple and portable multimeter for every electronics engineer.

- Auto range
- Duty cycle: 0.1%~99.9%
- Diode
- Auto power off
- Continuity buzzer
- Low battery indication: $\leq 2.4V$
- Data hold
- Relative mode



● UT120C

	Range	UT120A	UT120B	UT120C
Certificates	CE, RoHS, cETLus (UT120A/UT120B)			
DC voltage (V)	600V	$\pm(0.8\%+1)$	$\pm(0.8\%+1)$	$\pm(0.8\%+1)$
AC voltage (V)	600V	$\pm(1.2\%+3)$	$\pm(1.2\%+3)$	$\pm(1.2\%+3)$
DC current (A)	400mA			$\pm(1\%+3)$
AC current (A)	400mA			$\pm(1.5\%+5)$
Resistance (Ω)	40M Ω	$\pm(1\%+2)$	$\pm(1\%+2)$	$\pm(1\%+2)$
Capacitance (F)	100 μ F		$\pm(4\%+3)$	$\pm(4\%+3)$
Frequency (Hz)	100kHz	$\pm(0.5\%+3)$	$\pm(0.5\%+3)$	$\pm(0.5\%+3)$
Display count		4000	4000	4000
Category ratings	CAT II 600V			
Power	3V battery (CR2032)			
Display	43mm x 22mm			
Product net weight	76g			
Product size	110mm x 58.2mm x 10.8mm			
Standard accessories	Blister, English manual			
Standard individual packing	Gift box			
Standard quantity per carton	60pcs			
Standard carton measurement	430mm x 255mm x 460mm			
Standard carton gross weight	11.5kg			