

Standard motor mechanism module MT100/160, ComPacT NSX100/160, 220/240VAC 50/60Hz, 208/277VAC 60Hz

LV429434

Main

Device short name	MT250
Product or component type	Motor mechanism
Device application	Automatic spring charging
Range compatibility	ComPacT NSX100 new generation ComPacT NSX160 new generation ComPact NSX100 ComPact NSX160 ComPacT NSX DC new generation NSX100 DC ComPacT NSX DC new generation NSX160 DC Compact NSX100 DC Compact NSX100 DC Compact NSX160 DC PowerPact Multistandard EasyPact CVS250 PowerPact J PowerPact H
Control type	Standard
[Uc] control circuit voltage	208277 V AC 60 Hz 220240 V AC 50/60 Hz
Circuit breaker mounting mode	Fixed
Circuit breaker frame rated current	160 A 100 A

Complementary

Control signal type	Impulse Maintained
Circuit breaker response time	< 700 ms open < 80 ms closed
Maximum operating frequency	4 per minute
Maximum power consumption in VA	500 VA closing 500 VA opening
Provided equipment	SDE adaptor
Locking options description	Padlocking in OFF position 1 to 3 padlocks Ø 5 to Ø 8

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Weight	1.39 kg
Package 1 Height	11.7 cm

Package 1 width	10.5 cm
Package 1 Length	17.0 cm
Unit Type of Package 2	S04
Number of Units in Package 2	15
Package 2 Weight	21.526 kg
Package 2 Height	30.0 cm
Package 2 width	40.0 cm
Package 2 Length	60.0 cm

Offer Sustainability

Sustainable offer status	Green Premium product
REACh Regulation	REACh Declaration
EU RoHS Directive	Compliant EU RoHS Declaration
Mercury free	Yes
RoHS exemption information	Yes
China RoHS Regulation	China RoHS declaration Product out of China RoHS scope. Substance declaration for your information
Environmental Disclosure	Product Environmental Profile
Circularity Profile	End of Life Information
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
California proposition 65	WARNING: Cancer and Reproductive Harm - www.P65Warnings.ca.gov

Contractual warranty

Warranty 18 months